

4A	0 of 24 Assigned
4B	2 of 24 Assigned
BL1	0 of 8 Assigned
BL2	1 of 8 Assigned
BL3	0 of 6 Assigned
BR0	0 of 6 Assigned
BR1	0 of 4 Assigned
TL2	0 of 8 Assigned
TL3	0 of 8 Assigned

D	JTAG_VCCIO_SEL	CRESET_N	TMS	GND	Q0_TXDN0	VDDA_D_Q01	Q0_TXDN1	VD
E	GPIOB_P_16_CDI9_CLK3_P	GND	GPIOB_N_19_CBSELO	GND	GND	GND	GND	
F	GPIOB_P_11_CDI15	GPIOB_N_16_CDI8_CLK3_N	GPIOB_P_19_CBSEL1	GPIOB_N_22	GPIOR_127_C_LK8	GPIOR_130_P_LLN1	GPIOR_129_P_LLN1	GP EF
G	GPIOB_N_11_CDI14	GPIOB_P_04_EXTFB	GND	GPIOB_P_22_EXTFB	GPIOB_N_24_CDI4	GPIOB_P_24_CDI5_EXTFB	GPIOR_128_C_LK9	V

Add Exclude Pins

[Instruction] Instance(s) that is used by the pin in excluded pin list will be reset/ unassigned

Pin(s)

Type to search/ filter

Pin Number	Pin Name
Bank 2A	
AA19	GPIOT_P_02
AA20	GPIOT_N_00_CLK26_N
AA21	GPIOT_P_00_CLK26_P
AA24	GPIOT_P_10
AB20	GPIOT_N_04_CLK31_N
AB22	GPIOT_N_07
AB23	GPIOT_P_08
AC19	GPIOT_N_03_CLK30_N
AC20	GPIOT_P_04_CLK31_P
AC22	GPIOT_P_07
AC34	GPIOT_P_09

Exclude Pin(s)

Type to search/ filter

Pin Number	Pin Name
Bank 2A	
AA23	GPIOT_N_08
Bank 4B	
E1	GPIOB_P_16_CDI9_CLK3_P
Bank BR0	
F5	GPIOR_127_CLK8
F6	GPIOR_130_P_LLN1
F7	GPIOR_129_P_LLN1
F8	GPIOR_131_PERST_Q0_N
F9	GPIOR_132
G7	GPIOR_128_CLK9

OK Cancel

Information I/O Bank information Exclude

[Instruction] All excluded information will be listed here.

All Pins

+ Add - Remove - Remove All

Type to search/ filter

Pin Number	Pin Name
Bank 2A	
AA23	GPIOT_N_08
Bank 4B	
E1	GPIOB_P_16_CDI9_CLK3...
Bank BR0	
F5	GPIOR_127_CLK8
F6	GPIOR_130_P_LLN1
F7	GPIOR_129_P_LLN1
F8	GPIOR_131_PERST_Q0_N
F9	GPIOR_132
G7	GPIOR_128_CLK9

Right-click and
choose **Exclude Pin(s)**

Select Pins on Left and Click
Right Arrow to Exclude